



Mitas Generators

| Generator Model | G111 | | | G0111 | | | | 50 Hz | 60 Hz |
|---------------------------|--|----|----|--------------------|----|-----|-------------------------------|---|-----------------------|
| | Open Version | | | Soundproof Version | | | Voltage (V) | 230/400 | 220/380 |
| Dimensions cm (L x W x H) | 127 | 80 | 90 | 150 | 83 | 110 | Continuous Power (kVA) | 10,7 | 13,2 |
| Weight (kg) | 300 | | | 400 | | | Standby Power (kVA) | 11,8 | 14,85 |
| Fuel Tank (litres) | 67 | | | 77 | | | Power Factor | 0,8 | 0,8 |
| Manual Control Panel | Standard | | | Standard | | | Continuous Power (kWe) | 8,6 | 10,56 |
| Automatic Control Panel | Optional | | | Optional | | | Standby Power (kWe) | 9,44 | 11,88 |
| | | | | | | | Fuel Consumption (75% load) | 222 g/kWh 1,94 l/h | 220 g/kWh 2,34 l/h |
| Engine | 1 500 rpm | | | 1 800 rpm | | | Alternator | 1 500 rpm | 1 800 rpm |
| Model |  LOMBARDINI | | | | | | Model |  nsm generators | |
| | 9 LD 625-2 | | | | | | | T 132 XSB/4 | |
| Continuous Power (kWm) | 9,7 | | | 12,0 | | | Continuous Power | 10 | 12,5 |
| Standby Power (kWm) | 10,9 | | | 13,5 | | | Maximum efficiency | 81% | 82% |
| Aspiration | Natural | | | | | | Exciter | With Brush and compound transformer | |
| Cooling System | Air | | | | | | Wires | 6 | |
| Speed Governor | Mechanic | | | | | | Short-circuit current | 300% | |
| Number of Cylinders | 2, in Line | | | | | | Poles | 4 | 3F+N |
| Displacement | 1,248 l | | | | | | Insulation | H | IP23 |
| Bore x Stroke (mm) | 95x88 | | | | | | Voltage Regulation/ Condenser | ± 5% / Condenser | |

The values given in this datasheet are for information purposes only

